



PR
PORTABLE RANGE

PORTABLE GENERATOR GR3000

1 KEY FEATURES



Single phase



Gasoline



Grupel



50Hz




3000rpm

Continuous Power (PRP) (kW)	2.800
Starting Power (kW)	3.000
Frequency (Hz)	50
AC Voltage (V)	230
Automatic Voltage Regulator (AVR)	Yes
Fuel Tank Capacity (L)	15
Used fuel	Unleaded Petrol
Engine type	4 stroke
Starter system	Manual
Safety for lack of oil	Yes
Noise level (dBA)	96

DIMENSIONS

(L) Length (mm)	660
(W) Width (mm)	600
(H) Height (mm)	500
Weight while empty (kg)	52



EXTRAS

Sockets	2 16 amp schuko socket
Circuit Breaker	Yes
Hour Counter	Digital
Wheels and Handles	Yes
Battery	No

Voltmeter	Digital
Frequency meter	Yes
Auto Start	No
ATS	No
Command start	No

FRONT PANEL

