



50HZ 3000 RPM



PR
PORTABLE RANGE

PORTABLE GENERATOR GR6500

1 KEY FEATURES



Single Phase / Three Phase



Gasoline



Grupel



50Hz




3000rpm

Continuous Power (PRP) (kW)	6.300
Starting Power (kW)	6.900
Frequency (Hz)	50
AC Voltage (V)	400 / 230
Automatic Voltage Regulator (AVR)	Yes
Fuel Tank Capacity (L)	25
Used fuel	Unleaded Petrol
Engine type	4 stroke
Starter system	Manual / Electric
Safety for lack of oil	Si
Noise level (dBA)	97

DIMENSIONS

(L) Length (mm)	760
(W) Width (mm)	700
(H) Height (mm)	650
Weight while empty (kg)	104



EXTRAS

Sockets	1 16 amp schuko socket + 1 industrial single-phase socket + 1 3P socket + N + T 16 amp	Voltmeter	Digital
Circuit Breaker	Yes	Frequency meter	Yes
Hour Counter	Digital	Auto Start	Yes (via ATS Grupel)
Wheels and Handles	Yes	ATS	Yes- Single-phase and three-phase
Battery	Yes	Remote start	Yes

FRONT PANEL



REMOTE

