

OPTONICA



PORTABLE POWER STATION 400W SKU: 9418



Camera (16W)
Around 20 Recharges



Projector (100W)
Around 3.2 Hours



Camping light (125W)
Around 2.6 Hours



Macbook 12
Around 5 Recharges



Car Fridge (60W)
Around 5.4 Hours



Drone (40W)
Around 8 Recharges



Phone (4000mAh)
Around 27 Recharges



Rice cooker (330W)
Around 1.0 Hours



Electric fan (45W)
Around 7.2 Hours



Refrigerator (120W)
Around 2.7 Hours



Photography lights (300W)
Around 1.1 Hours

SPECIFICATIONS

Output		
AC output	Rated voltage	230V
	Rated power	400W
	Peak power	800W
	Frequency	50Hz
DC*2 Output	Rated voltage	13.3V
	Rated current	10A
DC Output Ciger Socket	Rated voltage	13.3V
	Rated current	10A
USB-A*3 Output	Rated voltage	5V
	Rated current	2.4A
USB-C*1 Output	PD: 60W Max	5V3A, 9V3A, 12V3A, 15V3A, 20V3A
Floodlight	mlm	200 Low / 800 Middle / 1400 high
Input		
DC Input	Rated voltage	12V-24V(12V 10A)
	Rated power	Max 120W
USB-C*1 Input	PD: 60W Max	5V3A, 9V3A, 12V3A, 15V3A, 20V3A
DC input and USB-C*1 input at the same time to recharge the power station, the input power can be up to 180W max		
Battery		
Rated capacity		320Wh
Battery cell type		Lithium-ion
General		
Working environment condition	Relative humidity: 20%-90%	
	Temperature: 32-104°F (-10-40°C)	
Size		237.2*195.2*190.6mm±5mm



CHARGE FIRST! Before using your new power station, plug it into a suitable power outlet until it is fully charged. Then you can start your exciting journey with it.